

## 2000 VA pure sine wave UPS, LCD display, 2 x Schuko + 3 x C13 outputs, USB, black

EG-UPS-PS2000-02

### ULTIMATE DEFENCE

- Pure sine wave output
- Provide backup power Prevents data loss
- Protects your sensitive and valuable equipment
- Perfect support for solar panel installations and other sensitive equipment that requires pure sinewave input
- Compact and reliable ideal for home and small office use



### Features

- Uninterruptable power supply with pure sine wave output
- USB interface
- Automatic AC voltage regulation (AVR)
- Intelligent overload and short-circuit protection
- Audible and visual alarms
- LCD display and LED status indication
- Internal battery with overcharge and over-discharge protection

### Packaging

|                                |                |
|--------------------------------|----------------|
| Q'ty in crtn, pcs              | 1              |
| Crtn volume, CUM               | 0.042075       |
| Crtn weight, kgs               | 19.73          |
| Individual package size LxWxH: | 492x316x236 mm |
| Carton size LxWxH:             | 510x330x250 mm |
| Country of origin              | CN             |
| Barcode                        | 8716309124812  |
| Customs code                   | 8504408590     |

### Package contents

UPS  
Power input cord

### Specifications

Type: line interactive with pure sine wave  
Waveform: pure sine, 5% distortion at linear load, PF > 0.8

Input: AC 220V±25%, 50Hz/60Hz ±10%  
Output: AC 220V±10%, 50Hz/60Hz ±1% (AC 220V±10% at inverter mode)  
Switching time: up to 10 ms typically  
Backup time: 10...30 mins (depends on the load)  
Battery: 151 x 65 x 94 mm, sealed lead-acid 12V/9Ah, F2 terminals x 3 pcs  
Charge time: up to 90% after 6-8 hours  
Sockets: C14 input, outputs: 3x IEC C13, 2x Schuko

### System requirements

In order to work correctly, the connected load should be at least 5% of the maximum capacity of the UPS. For example, a 700 W UPS needs at least a connected load of 35 W to work.

### Certificates

